N Se	/iFi Repeater tup instructions.		13:58 C @ @
<u>1.</u>	Screw the antenna onto the device.		Info Setup
<u>2.</u>	Power the device with a 5V transformer, USB-C connector. Then, the equipment will create an Access Point.	ē.	Restart Exit No AP set
<u>3.</u>	From a mobile phone, search for the MCSystems network and enter the following password: 12345678	lmag	11:44 @
	Once the phone is connected to the MCSystems network, the Configuration Portal <u>will</u> <u>automatically open</u> * (see image 1)		mcsystems CalmetMaurici MOVISTAR_4DD8 Calmet Taller MOVISTAR_9948
4.	Click on the Configure Wifi option from the main menu to set up the installation wifi network. In this section, all available networks will be scanned and displayed on the screen (see image 2).		SSID Password Show Password Save Refreeb
	Select the network to connect and enter the password. Then save the configuration by using the save button. Once saved, the device will connect and the following message will appear	Image 2	No AP set 11:39 ♥ ■ ■ ● ■ ● ● ● ● ● ● ● ● ● ● ● ● ● ● ●
5.	If the device remains connected to the MCSyst network, it means it could not connect to the configured WiFi. It is necessary to repeat the	గ ems లిజ <u>బ</u>	Saving Credentials Trying to connect ESP to network. If it fails reconnect to AP to try agai
*	If the portal does not open automatically, enter the following IP address in the browser: 192.168.4.1		

76%

86%

a al

اد م اد م اد م اد م

87% 🗎 :

Pol. Ind. La Canaleta, 3 253	300 Tàrrega (Spain)	RoHS	Setup instructions April 2025
info@mcsystems.es	(+34) 973 50 18 88	COMPLIANT	
www.mcsystems.es		CF MCSystems declares that the WiFi Repeater product	